

Key Features:

- 18 Solid Color Include:
- Red, Blue, Green, White, Yellow, Pink, Ice Blue, Purple and many more
- 1st-7th Color Cycle Flashing and Fading Modes.
- 1st-18th Color Flashing and Fading Mode.
- Brake override function

Brake override function allows the controller to interrupt color modes and activate only red while braking.

Remote Control Function:

A key:

This is the main function key, press it once, it shows a color pattern (1st-18th), in static mode, Long press the A key to the current LED stepless dimming.

B key:

The gradient or hopping mode (19th-20), long press B to achieve healthy color shift from slow to fast, in static mode (1st-18th), press B, lights from the current mode static to blink.

C key:

In the gradient or hopping mode (19th-20th), press C to achieve healthy color change from fast to slow, in static mode (1st-18th), press C, lights from the current mode static to change slowly fades.

D key:

Press D to control controller ON and OFF. At 2nd-18th color Press D key 3 seconds the system will be return 1st color (red).

Remote Distance: Max 30ft

Control Unit Description:

- Work Voltage: DC 12V.
- Control Type: Common Anode.
- Output Power: Max 40W.
- Connect the red power wire from the control box to the positive terminal of the battery.
- Connect the black ground wire to the negative terminal of the battery.
- Attach blue wire from controller to the positive brake light wire on the motorcycle.